Guide: Connecting Tuya Zigbee Module via Tuya Smart or Smart Life App (also compatible with other Zigbee-based apps)

With a Tuya Zigbee module, you can make your track lighting smart and easily controllable via your smartphone. Follow the steps below to pair the module through the app:

Requirements:

- A Tuya Zigbee module properly connected to the power rail (installed in the different light points)
- The Tuya Smart or Smart Life app (free in the App Store or Google Play)
- A Zigbee gateway (such as the Tuya Zigbee Hub)
- A stable Wi-Fi connection (2.4 GHz)

Step 1: Install the App and Create an Account

1. Download the Tuya Smart or Smart Life app.
2. Open the app and create an account, or log in with an existing account.

Step 2: Add the Zigbee Gateway (if not already done)

1. Make sure your Zigbee gateway is connected to power and Wi-Fi.
2. In the app: go to "Add Device" > select Zigbee Gateway (Zigbee Gateway Hub).
3. Follow the in-app instructions to add the gateway.

Step 3: Pair the Tuya Zigbee Module

1. Switch on the power to the rail. The module will automatically enter pairing mode (usually indicated by a blinking light).
2. Not blinking? Quickly toggle the power on and off several times or hold the reset button (if available) for 5 seconds.
3. In the app: tap "Add Device," select Zigbee-supported device, or allow the app to scan automatically.
4. Wait until the module is detected. Assign a name to the device (e.g., "Living Room Track Lighting").
5. Complete the process and test if you can control the lighting via the app.

Step 4: Automation & Voice Control (Optional)

- Connect with Google Assistant or Amazon Alexa for voice control.
- Create automations, such as schedules, sunset activation, or motion detection (if you use other Tuya sensors).

How to reset the lamps

1. Switch on the power to the rail
2. Press the switch 8 times in a row. Each switch interval is 2 seconds.
3. The light will flash on the 8th time, indicating that the reset is successful.

Tips:

- Keep the Zigbee gateway within approximately 10 meters of the module for the initial pairing.
- Want to control multiple spots or groups? You can add multiple modules and group them in the app.